7Dayshop - T6 CREE LED Torch

DS-045
User Manual

Quick Details

- LED Light Source: CREE XM-L T6 LED
- Flashlight Type: DS-045 Tactical Flashlight
- Brand Name: 7dayshop
- Battery Type: lithium battery
- Usage: Camping
- Power Source: Rechargeable Battery
- Lighting Period (h): 1.5 Full Beam
- Certification: CE, GS, RoHS, UL
- IP Rating: IP54
- Lamp Body Material: Anodized Aerospace-grade 6061T Aluminium Alloy
- Warranty(Year): 1
- EE XML T6 LED
- Brightness:: Full: 1200LM, Half: 600LM, Eco: 300LM, Strobe: 1200LM, SOS, 1200LM
- Working Time:: Full: 1.5-2h, Half: 3-4h, Eco: +6h
- Battery Type:: 2 x 18650 2200mAh battery
- Size:: 227x55(D)mm

Charging:

- Turn off the torch and remove the batteries.
- Insert the 2 x 18650 2200mAh Li-Ion batteries in to the charger making sure to match the (+) positive terminal on the charger with the (+) positive on the battery.
- Connect the charger to the mains socket and switch it on.
- The RED LED should illuminate on the charger to indicate the charging cycle has begun.
- The GREEN LED should illuminate once the batteries are full (1-3 hours).

Basic operation:

- Insert the 2 x 18650 batteries by unscrewing the switch cap at the rear of the flashlight. The batteries go in to the body (+) positive first.
- The ON/OFF button is located at the rear of the torch,
- When the ON/OFF button is fully depressed, the torch will cycle through the modes in the following order: (High, Off, Medium, Off, Low, Off, Flashing, Off, SOS).
- To quickly cycle through modes when the torch is in operation you can half depress the button which will skip between modes without the off cycle.